

DIGITAL WATT METER



F-WD2250A



F-WD2250B

Features

- Mono-phase and Tri-phase balance measures
- Small power measure
- Connection and operation simplicity
- Accuracy: better than 2% at the full current and voltage scale
- Protection against over-currents by fuses
- Over current and over Voltage indicator

Specifications

- Battery operated (F-WD2250B), AC operated (F-WD2250A)
- Automatic shutdown of the wattmeter after 2mins with battery saver
- The running time is about 8 hours in continuous operation
- Current ranges: 0.1A, 0.5A, 1A, 5A
- Voltage ranges: 3V, 15V, 30V, 240V, 450V
- Power measured: 0.3W~2250W (rate capacity)
- Frequency ranges: 0~3kHz
- LCD display: 3 ½ digits
- Dimensions: 235(W)×75(H)×170(D)mm
- Weight: 0.6kg